

AMPLIFIER FEATURES CHART

Amplifier Output Power Rating/ Channel	Model Numbers	Amp Channels	Input Types				Signal Processing					Music Muting			Night Ringer	Remote Volume	Output Meter	Mounting			Page Number
			TFL Input [†] 600-ohm Balanced	LMC Input [†] Lo-Z Balanced	ALX Input [†] Hi-Z Unbalanced	Balanced Inputs Hi-Z	Modular Inputs	Audio Enhancement	Loudness Contour	ALC	EQ	Bass/Treble	Tone Control	Variable Mute				Auto Mute	Manual Mute	Wall Mount	
1.5W	GA2	1			1													●			42
6W	GA6A	1		1	1													●			42
10W	C10	1	1	2 (1)	0 (1)													●	●		42
15W	TPU15A	1	1	1	1													●			43
20W	C20	1	1	2 (1)	0 (1)													●			42
35W	C35	1	1	2 (1)	1 (2)													●	●		42
35W	GS35	1	0 (1)	6 (4)	1 (2)													●	●		41
35W	TPU35B	1	1	1	1														●		43
35W	V35	1	●	●	●	8												●	●		38
60W	BPA60	1			●														●		46
60W	C60	1	1	2 (1)	1 (2)														●	●	42
60W	GS60	1	0 (1)	6 (4)	1 (2)														●	●	41
60W	TPU60B	1	1	1	1														●		43
60W	V60	1	●	●	●	8													●	●	38
100W	C100	1	1	2 (1)	1 (2)														●		42
100W	GS100	1	0 (1)	6 (4)	1 (2)														●	●	41
100W/60W/20W	PM3180	3	0 (1)	2 (1)	4														●	●	47
100W	TPU100B	1	1	1	1														●		43
100W	V100	1	●	●	●	8													●		38
100W	WV100	1	●	●	●	8													●		40
125W	HTA125A	1	●		●														●	●	46
150W	GS150	1	0 (1)	6 (4)	1 (2)														●	●	41
150W	V150	1	●	●	●	8													●	●	38
150W	WV150	1	●	●	●	8													●		40
250W	GS250	1	0 (1)	6 (4)	1 (2)														●		41
250W	HTA250A	1	●		●														●	●	46
250W	TPU250	1	1	1	1														●	●	43
250W	V250	1	●	●	●	8													●	●	38
250W	WV250	1	●	●	●	8													●		40
300/600W	M300	2/1	●	●	●	2													●		45
300W	X300	2	●			2													●	●	44
450/900W	M450	2/1	●	●	●	2													●	●	45
450W	X450	2	●			2													●	●	44
600/1200W	M600	2/1	●	●	●	2													●	●	45
600W	X600	2	●			2													●	●	44

● Feature Included

● Features determined by type of module installed

● Balanced input available with accessory plug-in transformer (TL100 or TL600)

● Accessory kit required for mounting

● Contact closure activation only

* Some inputs are switch selectable. The number in parentheses shows the maximum number of inputs when switched.

† BAL2S balanced input module included standard; uses one modular input bay.

Specifications subject to change without notice.

AMPLIFIER SPECS CHART



800.873.5528
WWW.TARGETD.COM

* @ -20dB FRP Transformer output;
@ FRP for Direct outputs

** Bandwidth limited to frequency response

*** FRP @ 120V AC line voltage

Specifications subject to change without notice.

Model Numbers	Output Power Rating/Channel	Channels	Frequency Response *	Distortion**	Speaker Outputs	AC Line Draw***	Dimensions	Product Weight
BP460	60W	1	20 Hz to 20 kHz	2% Max	8-ohm/25V, 16-ohm, 25VCT, 70V	180W	15-1/4" W x 3-1/2" H x 8-1/4" D	17 lb.
C10	10W	1	70 Hz to 16 kHz	1% Max	70V, 25V, 16-ohm, 8-ohm, 4-ohm	38W	11-3/8" W x 2-7/8" H x 7-3/8" D	5 lb.
C20	20W					50W		6 lb.
C35	35W	1	70 Hz to 16 kHz - Transformer; 20 Hz to 20 kHz - Direct	1% Max	70V, 25V, 16-ohm, 4-ohm direct 8-ohm on C35 and C60	85W	14-1/2" W x 3-3/4" H x 11" D	15 lb.
C60	60W					148W		17 lb.
C100	100W					220W		19 lb.
G42	1.5W	1	200 Hz to 15 kHz	2% Max	8- & 600-ohm	4W	5-1/2" W x 4-1/8" H x 2-1/4" D	2 lb.
G46A	6W	1	30 Hz to 12 kHz	2% Max	70V, 25V, 8-ohm	16W	8-1/2" W x 2-3/4" H x 6" D	5 lb.
GS35	35W	1	65 Hz to 20 kHz - Transformer; 20 Hz to 20 kHz - Direct	0.5% Max	70V, 25V, 25VCT, 8-ohm, 4-ohm direct	0.9A	16-1/2" W x 3-1/2" H x 13-1/2" D	17 lb.
GS60	60W					1.3A		20 lb.
GS100	100W					2.2A		23 lb.
GS150	150W					3.0A		29 lb.
GS250	250W	1	20 Hz to 20 kHz	0.5% Max	70V, 25VCT, 25V, 8-ohm, 4-ohm	5.0A	19" W x 5-1/4" H x 11" D	30 lb.
HTA125A	125W					260W		36 lb.
HTA250A	250W					520W		50 lb.
M300	300/600W	2 or 1	20 Hz to 20 kHz	0.5% Max	4- to 8-ohm (2 channel mode); 70V (1 channel mode)	12A	17" W x 3-1/2" H x 18-1/2" D (not including brackets)	41 lb.
M450	450/900W					15A		44 lb.
M600	600/1200W					20A		46 lb.
PM3180	100W 60W 20W	3	70 Hz to 20 kHz - Trans (Amp 1 & 2); 70 Hz to 15 kHz - Trans (Amp 3); 20 Hz to 20 kHz - Direct (Amp 1 & 2); 20 Hz to 15 kHz - Direct (Amp 3)	0.5% - Amp 1&2; 1% - Amp 3 (Max)	70V, 25V, 8-ohm, 4-ohm direct	430W	17" W x 5-1/2" H x 12-1/2" D	38 lb.
TPU15A	15W	1	70 Hz to 12 kHz	2% Max	70V, 25V, 8-ohm	0.5A	11" W x 2-3/4" H x 2-3/8" D	4 lb.
TPU35B	35W					0.75A		12 lb.
TPU60B	60W					1.5A		15 lb.
TPU100B	100W					2A		18 lb.
TPU250	250W					5A		28 lb.
V35	35W	1	45 Hz to 20 kHz - Transformer; 20 Hz to 20 kHz - Direct	0.5% - Transformer; 0.1% - Direct (Max)	70V, 25V, 8-ohm, 4-ohm direct	0.6A	17-1/4" W x 3-7/8" H x 14-3/4" D	22 lb.
V60	60W					1.3A		26 lb.
V100	100W					2.0A		28 lb.
V150	150W					3.5A		31 lb.
V250	250W					5.5A		32 lb.
WV100	100W	1	45 Hz to 20 kHz - Transformer; 20 Hz to 20 kHz - Direct	0.5% - Transformer; 0.1% - Direct (Max)	70V, 25V, 8-ohm, 4-ohm direct	2.0A	14-1/8" W x 21" H	27 lb.
WV150	150W					3.5A		29 lb.
WV250	250W					5.5A		28 lb.
X300	300W	2	20 Hz to 20 kHz	0.5% Max	70V direct	12A	17" W x 3-1/2" H x 18-1/4" D (not including brackets)	41 lb.
X450	450W					15A		44 lb.
X600	600W					20A		46 lb.